

## Bluetooth Contactless reader



- ✓ NFC TAG reader (T1T/T2T/T3T/T4T)
- ✓ Mifare Series, FeliCa
- ✓ S D K for Windows & Android
- ✓ Bluetooth wireless communication

### Applications

- Transportation: Contactless / NFC ticket management
- e-Purse & Loyalty : In-store coupon/loyalty management, Local payment
- Event /Festival visitor management

# DRAGON BT

Wireless contactless reader



DUALi Inc. Headquarter

1-309. INNOPLEX,  
#552 Wonchon-dong,  
Youngtong-gu, Suwon,  
Gyeonggi 443-380,  
Korea

Tel : 82-31-213-0074  
Fax : 82-31-213-0078  
URL : [www.duali.com](http://www.duali.com)

DUALi Inc. Sales Office

Tel : 82-070-4172-8585  
Fax : 82-2-562-8589  
E-mail : [sales@duali.com](mailto:sales@duali.com)

## Specifications

CPU	ARM 32-bit CPU
Program / Data Memory	128KBytes Flash / 20KBytes SRAM
Host Interface	Bluetooth v.2.1 + EDR Micro USB (Recharge & Communication)
Contactless Communication	ISO 14443 A/B, Mifare, DESFire, FeliCa, ISO15693 ISO 18092 4 tag type
Contact Communication	ISO 7816 compliant (SAM X 1EA)
Reading Distance	Maximum 5cm
User Interface	4 Status LED ( POWER, BLUETOOTH, RF, BATTERY ) Vibrator Buzzer
Battery	580mAh (5~6hours operation/ 14hours stand-by mode) Sleep mode (Awake button) Re-chargeable via micro USB cable
Dimension / Weight	60 X 103 X 11.5mm/ 47.5g
Operating Temperature	-10 ~ 60 °C